

**Amendments to the Claims:**

This listing of claims will replace all prior versions, and listings, of claims in the application. Please amend claims 24-25, and add new claim 30, as follows:

**Listing of claims:**

1. (previously presented) An analog multiplier for multiplying a first analog voltage signal at a first frequency by a second analog voltage signal at a second frequency, comprising:

a first stage for converting the first analog voltage signal into a first and a second current signals;

a second stage comprising a first and a second cross-coupled current-switching pairs, driven by the second voltage signal, said first and second current-switching pairs having respective current inputs for receiving the first and the second current signals, respectively;

parasitic capacitances associated with each of said current inputs of the current-switching pairs; and

a compensation circuit coupled to the current inputs of the current-switching pairs for compensating said parasitic capacitances at said first frequency.

2. (original) The analog multiplier of claim 1, in which an overall impedance of said compensation circuit and of said parasitic capacitances is substantially infinite at said first frequency.

3. (original) The analog multiplier of claim 2, in which said compensation circuit includes a filter designed in such a way to form, together with said parasitic capacitances, a resonating circuit associated with the current inputs of the current-switching pairs and acting a parallel resonator for differential-mode signals at a parallel resonance frequency substantially equal to the first frequency.

4. (original) The analog multiplier of claim 2, in which an overall impedance of said compensation circuit and of said parasitic capacitances is substantially zero at an integer multiple of said second frequency.

5. (previously presented) The analog multiplier of claim 3, in which said filter is further designed in such a way that said resonating circuit acts as a series resonator for common-mode signals at a series resonance frequency substantially equal to an integer multiple of the second frequency.

6. (original) The analog multiplier of claim 5, in which the filter includes a "T"-shaped LC filter, with a first inductive reactance element coupled to a first one of said current inputs, a second inductive reactance element coupled to a second one of said current inputs, and a capacitive reactance element coupled the first and second inductive reactance elements.

7. (original) The analog multiplier of claim 6, in which said first and second inductive reactance elements have a same inductive reactance value designed to make the parallel resonance frequency substantially equal to the first frequency, and the capacitive reactance element has a capacitive reactance value designed to make the series resonance frequency substantially equal to an integer multiple of the second frequency.

8. (previously presented) A method of improving linearity and reducing noise in an analog multiplier including a first stage for converting a first analog voltage signal at a first frequency into a first and a second current signals, and a second stage comprising a first and a second cross-coupled current-switching pairs, driven by a second voltage signal at a second frequency, said first and second current-switching pairs having respective current inputs for receiving the first and the second current signals, respectively, the method comprising:

compensating at said first frequency parasitic capacitances associated with said current inputs of the current-switching pairs.

9. (original) The method of claim 8, in which said compensating comprises associating with said current inputs a circuit creating parallel resonators resonating at a frequency substantially equal to the first frequency.

10. (original) The method according to claim 9, in which said compensating further comprises associating with said current inputs a circuit creating series resonators resonating at a frequency substantially equal to an integer multiple of the second frequency.

11. (previously presented) A mixer, comprising:

- an input stage having an output node and operable to receive an input signal having a first frequency;

- an output stage having an input node coupled to the output node and operable to receive a mixing signal having a second frequency; and

- a filter coupled to the output node and at the first frequency is operable to function as a tank circuit having a parallel resonant frequency that is substantially equal to the first frequency, and at a harmonic of the second frequency is operable to function as a tank circuit having a series resonant frequency substantially equal to the harmonic of the second frequency.

12. (original) The mixer of claim 11 wherein the input signal comprises a carrier signal having the first frequency and an information signal having a third frequency that is significantly lower than the first frequency.

13. (previously presented) A mixer, comprising:

- an input stage having first differential output nodes and operable to receive a differential input signal having a first frequency;

- an output stage having first differential input nodes respectively coupled to the differential output nodes and operable to receive a differential mixing signal having a second frequency; and

- a filter comprising an inductance directly coupling the differential output nodes and a capacitor coupled between the inductance and ground.

14. (original) The mixer of claim 13 wherein the input stage comprises:

- differential input nodes operable to receive the input signal;

- a current source;

a first transistor having a control node coupled to a first one of the differential input nodes, a first current conducting node coupled to the current source, and a second current conducting node coupled to a first one of the differential output nodes; and

a second transistor having a control node coupled to a second one of the differential input nodes, a first current conducting node coupled to the current source, and a second current conducting node coupled to a second one of the differential output nodes.

15. (original) The mixer of claim 13 wherein the input stage comprises:

differential input nodes operable to receive the input signal;

first and second current sources;

a first transistor having a control node coupled to a first one of the differential input nodes, a first current conducting node coupled to the first current source, and a second current conducting node coupled to a first one of the differential output nodes;

a second transistor having a control node coupled to a second one of the differential input nodes, a first current conducting node coupled to the first current source, and a second current conducting node coupled to a second one of the differential output nodes;

a third transistor having a control node coupled to the first one of the differential input nodes, a first current conducting node coupled to the second current source, and a second current conducting node coupled to the first one of the differential output nodes; and

a fourth transistor having a control node coupled to the second one of the differential input nodes, a first current conducting node coupled to the second current source, and a second current conducting node coupled to the second one of the differential output nodes.

16. (original) The mixer of claim 13 wherein the output stage comprises:

second differential input nodes operable to receive the mixing signal;

second differential output nodes;

a first transistor having a control node coupled to a first one of the second differential input nodes, a first current conducting node coupled to a first one of the

first differential input nodes, and a second current conducting node coupled to a first one of the second differential output nodes;

a second transistor having a control node coupled to a second one of the second differential input nodes, a first current conducting node coupled to the first one of the first differential input nodes, and a second current conducting node coupled to a second one of the second differential output nodes;

a third transistor having a control node coupled to the second one of the second differential input nodes, a first current conducting node coupled to a second one of the first differential input nodes, and a second current conducting node coupled to the first one of the second differential output nodes; and

a fourth transistor having a control node coupled to the first one of the second differential input nodes, a first current conducting node coupled to the second one of the first differential input nodes, and a second current conducting node coupled to the second one of the second differential output nodes.

17. (original) The mixer of claim 13, further comprising:

a reference node; and

wherein the filter comprises,

a first inductive element having a first node coupled to a first one of the first differential output nodes of the input stage and having a second node,

a second inductive element having a first node coupled to a second one of the first differential output nodes and having a second node, and

a capacitive element having a first node coupled to the second nodes of the first and second inductive elements and having a second node coupled to the reference node.

18. (original) The mixer of claim 13, further comprising:

a reference node; and

an inductive element having first and second nodes respectively coupled to the first differential output nodes of the input stage and having a tap, and

a capacitive element having a first node coupled to the tap and having a second node coupled to the reference node.

19. (original) The mixer of claim 13 wherein the harmonic comprises a second harmonic of the second frequency.

20. (previously presented) An electronic system, comprising:

an oscillator operable to generate an oscillator signal having a second frequency;

a mixer, comprising,

an input stage having an output node and operable to receive an input signal having a first frequency,

an output stage having a first input node coupled to the output node, having a second input node coupled to the oscillator, and having an output node, and

a filter coupled to the first input node of the output stage and at the first frequency is operable to function as a tank circuit having a parallel resonant frequency that is substantially equal to the first frequency, and at a harmonic of the second frequency is operable to function as a tank circuit having a series resonant frequency substantially equal to the harmonic of the second frequency; and

a load coupled to the output node of the output stage.

21. (previously presented) A method, comprising:

mixing a first signal having a first frequency with a second signal having a second frequency to generate a resulting signal having a linearity and a component having a third frequency that is a harmonic of the second frequency;

generating a parallel resonant frequency that is substantially equal to the first frequency; and

generating a series resonant frequency substantially equal to the third frequency.

22. (previously presented) The method of claim 21 wherein generating a parallel resonant frequency comprises increasing the impedance at the first frequency.

23. (previously presented) The method of claim 21 wherein generating a series resonant frequency comprises decreasing the impedance at the third frequency.

24. (currently amended) A circuit, comprising:

a differential input stage having first and second input nodes operable to receive a signal having a first frequency and first and second output nodes that respectively have first and second capacitances; and

a filter coupled to the first and second output nodes and ~~comprising a parallel tank circuit having an element that forms~~operable to form at substantially the first frequency a first and second parallel resonant tank circuit circuits with the first and second capacitances, respectively.

25. (currently amended) The circuit of claim 24 wherein the input stage further comprises first and second output nodes operable to receive a signal having a second frequency, and wherein the filter is operable as a parallel resonant circuit at the first frequency and is operable as a series resonant circuit at the second frequency to form at substantially the second frequency first and second series resonant tank circuits with the first and second capacitances, respectively.

26. (previously presented) A method, comprising:

mixing a first signal having a first frequency with a second signal having a second frequency with a mixer having an input stage coupled to an output stage at first and second nodes;

generating a parallel resonant frequency that is substantially equal to the first frequency; and

generating a series resonant frequency substantially equal to the second frequency.

27. (previously presented) The method of claim 26 wherein generating a parallel resonant frequency comprises forming first and second parallel resonant circuits between the reference node and the first and second nodes, respectively, at the first frequency.

28. (previously presented) The method of claim 26 wherein generating a series resonant frequency comprises forming first and second series resonant circuits between the reference node and the first and second nodes, respectively, at the second frequency.

29. (previously presented) The mixer of claim 13 wherein the inductance comprises first and second inductors.

30. (new) The circuit of claim 25, further comprising:

a reference node; and

wherein the filter comprises:

a first inductive element having a first node coupled to a first one of the first differential output nodes of the input stage and having a second node,

a second inductive element having a first node coupled to a second one of the first differential output nodes and having a second node, and

a capacitive element having a first node coupled to the second nodes of the first and second inductive elements and having a second node coupled to the reference node.